



Main

For independent control of 8 blind/roller shutter drives. The functions of the blind channels is freely configurable. All blind outputs can be operated manually using push-buttons. With integrated bus coupler. For installation on DIN rails EN 50022.

Complementary

The bus is connected using a bus connecting terminal; a data rail is not necessary. Channel status display via LEDs. A green LED indicates readiness for operation.

KNX software functions:

Blind functions: Blind type. Running time. Idle time. Step interval. Differentiated disable functions and weather alarms. 8-bit positioning for height and slat. Scenes. Manual/automatic mode. Differentiated status and status feedback functions.

For each blind output:

Nominal voltage: AC 230 V, 50 - 60 Hz

Nominal current: 10 A, $\cos\phi = 0.6$

Motor load: AC 230 V, max. 1000 W

External auxiliary voltage (optional): AC 110-240 V, 50-60 Hz, max. 2 VA

Device width: 8 modules = approx. 144 mm

Contents: With bus connecting terminal and cable cover.

Colour: light grey

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.