

Product Page Neo-THC-x

Temperature Humidity Control 4 Binary Inputs / Outputs



Product Page

The KNX-Sensor Neo-THC-x is used for measuring and controlling indoor air parameters

- Air temperature (sensor in the housing) also weighted with external temperature
- · Humidity (sensor in the housing)
- Calculated values absolute humidity, dew point temperature and energy content (enthalpy)
- Control functions for heating and cooling applications (can be combined)
- Setpoint temperatures for Comfort, Standby, Economy and Protection, selectable via KNX HVAC objects
- · Setpoint change via objects
- · Storage of minimum- and maximum-temperature
- Heat- and frost-alarm
- · Limits for temperature and humidity
- · Fan control by humidity limits and external inputs
- Detecting of dew point temperature and alarm / regulation at risk of condensation
- · Adaptation for setpoint and maximum temperatures
- Controller output 0...100% or programmable PWM for thermal actuators
- · Valve rinse function
- Second temperature controller as auxiliary controller

Four binary inputs / outputs (floating)

- · Light control as switch / button with short, long, double and both function
- Dimmer
- · Blind and shutter control
- Programmable Encoder
- Temperature adjustment
- The binary inputs can be configured as outputs (LED / Beeper)

Four logic blocks for the logical link between internal and external signals.

- 10 associated logic inputs / outputs
- Heat- and cooling-request as additionally available signals
- Functions "AND, OR, NOT, XOR" for binary logic
- Functions "+ *" for 8-bit values
- Function "=" for conditional forwarding of events

Applications

- · Detection and control of room temperature and humidity
- Decentralized control for steady KNX-valves or thermal actuators
- · Decentralized ventilation control depending on humidity
- Evaluation of external switches and push buttons for switching functions





e1

Subject to change Page 1

 Arcus-EDS GmbH
 Rigaer Str. 88 , 10247 Berlin
 Tel.: +49 / (0)30 / 2593 3914

 www.arcus-eds.de
 sales@arcus-eds.de
 Fax.: +49 / (0)30 / 2593 3915



Product Page Neo-THC-x

Temperature Humidity Control 4 Binary Inputs / Outputs



e1

Startup


The KNX Sensor is set up using the ETS (Version 4 or higher) and the applicable application program.

Application for ETS from version 3f on request.

The sensor is delivered unprogrammed.

All functions are programmed and parameterized with ETS.

Please read the ETS instructions.



Assembly

The **Neo-THC-x** sensor is designed for mounting in a standard flush-mounted socket (60/68) mm and is located in an IP20 plastic housing with aluminum cover.

In Case of Bus Voltage Recurrence

All changes made using the help key for the KNX bus are saved if the device has been correctly parameterized..

By using the weighted mixture temperature, the external temperature scaling is set to 0% until an external temperature value is received.

The measuring and control values start with their current values (integral component=0 by PI-Controller).

The ETS parameter settings are retained.

Discharge Program and Reset Sensor

In order to delete the programming (projecting) and to reset the module back to delivery status, it must be switched off (disconnect the KNX bus).

Press and hold the programming button while reconnecting the KNX bus and wait until the programming LED lights up (approx. 5-10 seconds).

Now you can release the programming button.

The module is ready for renewed projecting.

If you release the programming button too early, repeat the aforementioned procedure.

Subject to change Page 2



Product Page Neo-THC-x

Temperature Humidity Control 4 Binary Inputs / Outputs



Technical Data

Technical Data - Neo-THC-x

Measurement	Temperature, rel. Humidity Temperature (PT1000, external)
Calculated Values	abs. Humidity, Dewpoint Temperature, Enthalpie
Control	integrated
Temperature Range	-20 +80°C
Accuracy	± 0,3°C
Resolution	± 0,01°C
Humidity Range	0 95% r.H
Accuracy	± 3% r.H (2080%) at +20°C, else ± 5% r.H
Binary In- / Output	4
Operating Voltage	KNX Bus Voltage 21 32VDC
Power Consumption	approx. 240mW (at 24VDC)
Environment Temperature KNX-Module	Storage: -20 +85°C Operating: -20 +80°C
Environment Humidity KNX-Module	0 95% r.H Non Condensing
Bus Coupler	integrated
Auxiliary Supply	not required
Startup with the ETS Version 4 or higher	HLK305
Curcuit Points	KNX 2-pole clamps (red / black)
Protection Class	IP20
Housing KNX-Module	Cover aluminum anodized (black) square: (80 x 80 x 6) mm round: Ø 84 x 6 mm Standard flush-mounted socket (60/68 mm) in the dry interior
Article Number	30531583 Aluminum, square, sanded 30531584 Aluminum, square, sanded, black 30531683 Aluminum, round, anodized 30531684 Aluminum, round, anodized, black



arcus-eds | KNX

Product Page Neo-THC-x

Temperature Humidity Control 4 Binary Inputs / Outputs



e1

Imprint

Editor: Arcus-EDS GmbH, Rigaer Str. 88, 10247 Berlin

Responsible for the contents: Hjalmar Hevers, Reinhard Pegelow

Reprinting in part or in whole is only permitted with the prior permission of Arcus-EDS GmbH.

All information is supplied without liability. Technical specifications and prices can be subject to change.

Liability

The choice of the devices and the assessment of their suitability for a specified purpose lie solely in the responsability of the buyer. Arcus-EDS does not take any liability or warranty for their suitability. Product specifications in catalogues and data sheets do not represent the assurance of certain properties, but derive from experience values and measurements. A liability of Arcus-EDS for damages caused by incorrect operation/projecting or malfunction of devices is excluded. The operator/project developer has to make sure that incorrect operation, planning errors and malfunctions cannot cause subsequent damages.

Safety Regulations

Attention! Installation and mounting must be carried out by a qualified electrician.

The buyer/operator of the facility has to make sure that all relevant safety regulations, issued by VDE, TÜV and the responsible energy suppliers are respected. There is no warranty for defects and damages caused by improper use of the devices or by non-compliance with the operating manuals.

Warranty

We take over guarantees as required by law.

Please contact us if malfunctions occur. In this case, please send the device including a description of the error to the company's address named below.

Manufacturer



Registered Trademarks



The CE trademark is a curb market sign that exclusively directs to autorities and does not include any assurance of product properties.



Registered trademark of the Konnex Association.

Subject to change Page 4