



Main

For System M.

Movement detector for indoors.

When a movement is detected, a data telegram defined by the programming is transmitted.

Complementary

With integrated bus coupling unit.

KNX software functions:

Five movement blocks: up to four functions can be triggered per block. Telegrams: 1 bit, 1 byte, 2 bytes.

Normal operation, master, slave, safety pause, disable function. Sensitivity, brightness and staircase timer can be set using the ETS or the potentiometer. Self-adjusting staircase timer.

Angle of detection: 180°

Range: 8 m (for mounting height of 1.1 m)

Number of levels: 1

Number of zones: 14

Sensitivity: infinitely adjustable (ETS or potentiometer)

Light sensor: infinitely adjustable from approx. 10 to 2000 Lux (ETS or potentiometer)

Time: adjustable in steps from 1 s to 8 min (potentiometer) or adjustable from 1 s to 255 hours (ETS)

EC Directives: Low-voltage guideline 2006/95/EC and EMC guideline 2004/108/EC

Contents: With bus connecting terminal and supporting plate.

Material : Thermoplastic brilliant

Colour: polar white, glossy